

2N4401




Low Power Bipolar Transistors



Features:



- NPN Silicon Planar Epitaxial Transistors.
- General Purpose Switching Applications.

TO-92 Plastic Package



Dimensions	Minimum	Maximum
A	4.32	5.33
B	4.45	5.20
C	3.18	4.19
D	0.41	0.55
E	0.35	0.50
F	5°	
G	1.14	1.40
H		1.53
K	12.70	-
L	1.982	2.082

Dimensions : Millimetres



Pin Configuration:

1. Emitter
2. Base
3. Collector



2N4401



Low Power Bipolar Transistors

Absolute Maximum Ratings

Rating	Symbol	2N4401	Unit
Collector-Emitter Voltage	V_{CEO}	40	V
Collector-Base Voltage	V_{CBO}	60	
Emitter-Base Voltage	V_{EBO}	6	
Collector Current Continuous	I_C	600	mA
Power Dissipation at $T_a = 25^\circ\text{C}$ Derate above 25°C	P_D	625 5.0	mW mW/ $^\circ\text{C}$
Power Dissipation at $T_c = 25^\circ\text{C}$ Derate above 25°C		1.5 12	W W/ $^\circ\text{C}$
Operating and Storage Junction Temperature Range	T_j, T_{stg}	-55 to +150	$^\circ\text{C}$
Thermal Resistance			
Junction to Case	$R_{th(j-c)}$	83.3	$^\circ\text{C/W}$
Junction to Ambient	$R_{th(j-a)}$	200	

Electrical Characteristics ($T_a = 25^\circ\text{C}$ unless otherwise specified)

Characteristic	Symbol	2N4401	Unit
Collector Emitter Voltage $I_C = 1\text{mA}, I_B = 0$	BV_{CEO}^*	>40	V
Collector Base Voltage $I_C = 100\mu\text{A}, I_E = 0$	BV_{CBO}	>60	
Emitter Base Voltage $I_E = 100\mu\text{A}, I_C = 0$	BV_{EBO}	>6	
Base Cut off Current $V_{CE} = 35\text{V}, V_{EB} = 0.4\text{V}$	I_{BEV}	<0.1	μA
Collector Cut off Current $V_{CE} = 35\text{V}, V_{EB} = 0.4\text{V}$	I_{CEX}		
Collector Emitter Saturation Voltage $I_C = 150\text{mA}, I_B = 15\text{mA}$ $I_C = 500\text{mA}, I_B = 50\text{mA}$	$V_{CE(Sat)}^*$	<0.4 <0.75	V
Base Emitter Saturation Voltage $I_C = 150\text{mA}, I_B = 15\text{mA}$ $I_C = 500\text{mA}, I_B = 50\text{mA}$	$V_{BE(Sat)}^*$	0.75 - 0.95 <1.2	

*Pulse Test : Pulse Width: $\leq 300\mu\text{s}$, Duty $\leq 2.0\%$



2N4401



Low Power Bipolar Transistors

Electrical Characteristics ($T_a = 25^\circ\text{C}$ unless otherwise specified)

Characteristic	Symbol	2N4401	Unit
DC Current Gain $I_C = 0.1\text{mA}, V_{CE} = 1\text{V}$ $I_C = 1\text{mA}, V_{CE} = 1\text{V}$ $I_C = 10\text{mA}, V_{CE} = 1\text{V}$ $I_C = 150\text{mA}, V_{CE} = 1\text{V}^*$ $I_C = 500\text{mA}, V_{CE} = 2\text{V}^*$	h_{FE}	>20 >40 >80 100 - 300 >40	-
Dynamic Characteristics			
Small Signal Current Gain $I_C = 1\text{mA}, V_{CE} = 10\text{V}, f = 1\text{KHz}$	h_{fe}	40 - 500	-
Input Impedance $I_C = 1\text{mA}, V_{CE} = 10\text{V}, f = 1\text{KHz}$	h_{ie}	1.0 - 15	k Ω
Voltage Feedback Ratio $I_C = 1\text{mA}, V_{CE} = 10\text{V}, f = 1\text{KHz}$	h_{re}	0.1 - 8.0	$\times 10^{-4}$
Output Impedance $I_C = 1\text{mA}, V_{CE} = 10\text{V}, f = 1\text{KHz}$	h_{oe}	1.0 - 30	$\mu\Omega$
Collector-Base Capacitance $V_{CB} = 5\text{V}, I_E = 0, f = 100\text{KHz}$ $V_{CB} = 10\text{V}, I_E = 0, f = 140\text{KHz}$	C_{cb}	<6.5 -	pF
Emitter-Base Capacitance $V_{EB} = 0.5\text{V}, I_C = 0, f = 100\text{kHz}$	C_{eb}	<30	
Transition Frequency $I_C = 20\text{mA}, V_{CE} = 10\text{V}, f = 100\text{MHz}$	f_T	>250	MHz
Switching Characteristics			
$V_{CC} = 30\text{V}, V_{EB} = 2\text{V}$ $I_C = 150\text{mA}, I_{B1} = 15\text{mA}$			
Delay Time	t_d	<15	ns
Rise Time	t_r	<20	
$V_{CC} = 30\text{V}, I_C = 150\text{mA}$ $I_{B1} = I_{B2} = 15\text{mA}$			
Storage time	t_s	<225	ns
Fall Time	t_f	<30	


*Pulse Test : Pulse Width: $\leq 300\mu\text{s}$, Duty $\leq 2.0\%$

2N4401


Low Power Bipolar Transistors




DC Current Gain



DC Current Gain



On Voltages




2N4401


Low Power Bipolar Transistors



DC Current Gain



Collector Saturation Region




2N4401

Low Power Bipolar Transistors



On Voltages



Part Number Table

Package	Part Number
TO-92	2N4401



2N4401

Low Power Bipolar Transistors



Notes:

International Sales Offices:

 AUSTRALIA - Farnell Tel No: ++61 1300 361 005 Fax No: ++61 1300 361 225	 FINLAND - Farnell Tel No: ++ 358 9 560 7780 Fax No: ++ 358 9 345 5411	 ITALY - Farnell Tel No: ++ 39 02 93 995 200 Fax No: ++ 39 02 93 995 300	 SPAIN - Farnell Tel No: 901 20 20 80 Fax No: 901 20 20 90
 AUSTRIA - Farnell Tel No: ++ 43 662 2180 680 Fax No: ++ 43 662 2180 670	 FRANCE - Farnell Tel No: ++ 33 474 68 99 99 Fax No: ++ 33 474 68 99 90	 MALAYSIA - Farnell-Newark Tel No: ++ 60 3 7873 8000 Fax No: ++ 60 3 7873 7000	 SWEDEN - Farnell Tel No: ++ 46 8 730 50 00 Fax No: ++ 46 8 83 52 62
 BELGIUM - Farnell Tel No: ++ 32 3 475 2810 Fax No: ++ 32 3 227 3648	 GERMANY - Farnell Tel No: ++ 49 89 61 39 39 39 Fax No: ++ 49 89 613 59 01	 NETHERLANDS - Farnell Tel No: ++ 31 30 241 7373 Fax No: ++ 31 30 241 7333	 SWITZERLAND - Farnell Tel No: ++ 44 204 64 64 Fax No: ++ 44 204 64 54
 BRAZIL - Farnell-Newark Tel No: ++ 55 11 4066 9400 Fax No: ++ 55 11 4066 9410	 HONG KONG - Farnell-Newark Tel No: ++ 852 2268 9888 Fax No: ++ 852 2268 9899	 NEW ZEALAND - Farnell Tel No: 0800 90 80 80 Fax No: 0800 90 80 81	 UK - Farnell Tel No: ++ 44 8701 200 200 Fax No: ++ 44 8701 200 201
 CHINA - Farnell-Newark Tel No: ++86 10 6238 5152 Fax No: ++86 10 6238 5022	 HUNGARY - Farnell Tel No: ++ 44 870 1200 208 Fax No: ++ 44 870 1200 209	 NORWAY - Farnell Tel No: 800 146 70 Fax No: 800 146 76	 UK - CPC ++ 44 8701 202 530 ++ 44 8701 202 531
 CZECH REPUBLIC - Farnell Tel No: ++ 44 870 1200 208 Fax No: ++ 44 870 1200 209	 INDIA - Farnell Tel No: ++ 44 870 1200 208 Fax No: ++ 44 870 1200 209	 PORTUGAL - Farnell Tel No: ++ 34 93 475 8804 Fax No: ++ 34 93 474 5288	 USA - Newark Tel No: 800 463 9275
 DENMARK - Farnell Tel No: ++ 45 44 53 66 44 Fax No: ++ 45 44 53 66 06	 IRELAND - Farnell Tel No: ++ 353 1 830 9277 Fax No: ++ 353 1 830 9016	 RUSSIA - Farnell Tel No: ++ 44 870 1200 208 Fax No: ++ 44 870 1200 209	 EXPORT - Farnell Tel No: ++ 44 8701 200 208 Fax No: ++ 44 8701 200 209 For enquiries from all other markets
 ESTONIA - Farnell Tel No: ++ 358 9 560 7780 Fax No: ++ 358 9 345 5411	 ISRAEL - Farnell Tel No: ++ 180 937 0015 Fax No: ++ 180 937 0014	 SINGAPORE - Farnell-Newark Tel No: ++ 65 6788 0200 Fax No: ++ 65 6788 0300	http://www.farnell.com http://www.newark.com http://www.cpc.co.uk

Disclaimer This data sheet and its contents (the "Information") belong to the Premier Farnell Group (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. SPC Multicomp is the registered trademark of the Group. © Premier Farnell plc 2008.

